

RING AGAIN

If you hear a busy tone when dialing another extension and want the system to call you back when their line is free:
From busy tone:

Press **SWITCHHOOK or Flash**

Hear special dial tone

Dial *75

Hear confirmation tone

Hang up

To answer a call ringing back to your station:

Lift handset

Hear ringing connection being sent to other station.

To cancel a call back request:

Lift handset

Dial #75

Hear confirmation tone

Hang up

Note: If you do not respond to Ring Again recall within 4 rings feature automatically cancels.

LAST NUMBER REDIAL

Lift handset

Press ##

SYSTEM TONES

Special dial tone:

Three beeps followed by a steady dial tone. This is heard after the **SWITCHHOOK** is pressed and is your indication that you may proceed with feature activation.

Confirmation tone:

Two short bursts of tone followed by silence. This is heard after a feature access code has been entered and indicates the feature has been successfully activated.

Reorder tone:

A rapid busy signal that indicates you have attempted to activate a restricted feature or have entered an access code incorrectly.

DISTINCTIVE RINGING

Calls from within the system:

You will hear a long ring

Calls from outside the system:

You will hear a long ring followed by one short ring.

Ring Again (Call Back) Recall:

You will hear a long ring followed by two short rings.

TELECOM
Box 1885
3-2007



TELEPHONE USER GUIDE

SINGLE LINE SET

FOR REPAIR, DIAL 0

PLACING CALLS

Within the system:

Lift handset

Dial 5 digit extension

Outside the system:

Dial 8+ telephone number

HOLD

To place a call on hold:

Press **SWITCHHOOK**

Hear special dial tone

Dial *74

Do Not Hang Up

To retrieve held call:

Hang up

Your call will ring back to you

TRANSFER

To transfer a call to another extension:

Press **SWITCHHOOK (or flash)**

Hear special dial tone

Dial 5-digit extension number

Announce call, press flash again

Hang up

If extension is busy or does not answer:

Press **SWITCHHOOK** twice

You are reconnected to the first party

CALL PARK

To park a call against your extension number so that it can be retrieved from another telephone:

To park:

Ask party to hold

Press **SWITCHHOOK**

Hear special dial tone

Dial *78

Hear confirmation tone

Hang up

To retrieve from any telephone:

Lift handset

Hear dial tone

Dial #78

Hear special dial tone

Dial extension number call parked against

CALL WAITING

To answer your call waiting signal

Ask first party to hold

Depress **SWITCHHOOK**

Original call is now on hold

You are connected to the second call

Cancel Call Waiting

To temporarily turn off the call waiting feature for one call:

Before placing call, lift handset

Dial *70

3-WAY CONFERENCE

To add a third party to an existing call:

Ask first party to hold

Press **SWITCHHOOK (or flash)**

Hear special dial tone

Dial third party's number

When party answers

Press **SWITCHHOOK (or flash)**

All three parties are connected

To drop the last call and continue speaking with first party:

Press **SWITCHHOOK (or flash)**

CALL PICKUP

To answer an incoming call ringing at another extension number within your call pick up group:

Lift handset

Hear dial tone

Dial *77

You are connected to incoming call

CALL FORWARD (BUSY)

Lift handset

Dial *71 and the 5 digits you are forwarding to

To cancel:

Lift Handset

Dial #71

CALL FORWARD (AFTER 3 RINGS)

Lift handset

Dial *73 and the 5 digits you are forwarding to

To cancel:

Lift handset

Dial #73

CALL FORWARDING-ALL CALLS

To temporarily redirect your incoming calls to another extension:

Lift handset

Hear dial tone

Dial *72

Hear special dial tone

Dial 5-digits you are forwarding to

Wait for confirmation tone

Hang up

To cancel:

Lift handset

Hear dial tone

Dial #72

Listen for confirmation tone