

7841 Phone Quick Start Guide

sharon roy - 2016-06-17 - Comments (0) - Cisco 7841

To learn more about the 7841, go [here](#).



1. **Handset light:** incoming call flashes red; message waiting solid red
2. **Phone screen:** displays status, feature and call information
3. **Line buttons:** active call solid green; held call flashing green; incoming call flashing amber; shared line in use solid red
4. **Softkeys:** displays options associated with feature in use
5. **Navigation pad and select button:** use to scroll through menus; while on hook, press up to display call history
6. **Hold:** places call on hold and retrieves held call
7. **Conference:** initiates a conference call
8. **Transfer:** initiates a call transfer
9. **Speakerphone:** activates (solid green) and deactivates
10. **Headset:** activates (solid green) and deactivates
11. **Mute:** deactivates (solid red) and reactivates microphone
12. **Volume:** adjusts ringer on-hook and voice volume off-hook
13. **Contacts:** Brown directory access
14. **Applications:** call history, preferences
15. **Messages:** auto-dial access to voicemail

Using Voice Mail

Call voicemail from your desk:

1. Press the Messages button
2. Enter your PIN followed by #
Mailbox ID: 5-digit extension
Starter PIN: 864236

Call voicemail from outside:

1. Dial 401-863-9000
2. Press #
3. Enter your Mailbox ID, then #
4. Enter your PIN, then #

	During Message Review	After Message Review																								
Press 1: Play New Messages	<table border="1"> <tr> <td>Rewind 1</td> <td>Pause 2</td> <td>F. Fwd 3</td> </tr> <tr> <td>Slow 4</td> <td>Vol. 5</td> <td>Fast 6</td> </tr> <tr> <td>Delete 7</td> <td>8</td> <td>Save 9</td> </tr> <tr> <td>Cancel *</td> <td>Help 0</td> <td>End #</td> </tr> </table>	Rewind 1	Pause 2	F. Fwd 3	Slow 4	Vol. 5	Fast 6	Delete 7	8	Save 9	Cancel *	Help 0	End #	<table border="1"> <tr> <td>Rewind 1</td> <td>2</td> <td>3</td> </tr> <tr> <td>Replay 4</td> <td>Prop. 5</td> <td>Fwd 6</td> </tr> <tr> <td>Delete 7</td> <td>Reply 8</td> <td>Save 9</td> </tr> <tr> <td>Cancel *</td> <td>Help 0</td> <td>Skip #</td> </tr> </table>	Rewind 1	2	3	Replay 4	Prop. 5	Fwd 6	Delete 7	Reply 8	Save 9	Cancel *	Help 0	Skip #
Rewind 1	Pause 2	F. Fwd 3																								
Slow 4	Vol. 5	Fast 6																								
Delete 7	8	Save 9																								
Cancel *	Help 0	End #																								
Rewind 1	2	3																								
Replay 4	Prop. 5	Fwd 6																								
Delete 7	Reply 8	Save 9																								
Cancel *	Help 0	Skip #																								
Press 2: Send a Message	<ol style="list-style-type: none"> 1. Record your message, then # 2. Enter the extension, then # 3. Press # to confirm 4. Press 9 + 1 to add a name 5. Press # to send or choose from a message option 	Message Options: 1 Mark as urgent 2 Request return receipt 3 Mark as private 4 Set future delivery 5 Review recording 6 Re-record message 7 Add to the message # Send message																								
Press 4: Setup Options	Press 1 — Preferences Press 1 — PIN Press 2 — Recorded name Press 2 — Message Settings Press 1 — Message notification Press 3 — Menu style Press 4 — Private lists Press 3 — Greetings Press 1 — Edit the standard greeting Press 2 — Turn on/off alternate greeting Press 3 — Edit other greetings Press 4 — Play all greetings	<div style="border: 1px solid black; padding: 5px;"> Tips: * Exit or back up ## Number and spelling entry toggle </div>																								

Placing Calls

To place a call:

1. Lift handset *or*
Press **Speaker** button *or*
Press **Headset** button *or*
Press **New Call** softkey *or*
Press a line button
2. Dial the number

To place a second call on same line:

1. Press **Hold**
2. Press **New Call** softkey
3. Dial the number

To call an extension:

Dial 5-digit extension

To call Brown Switchboard:

Dial 0

To call external number:

Dial 8 + 1 + telephone number

To call international number:

Dial 8 + 011 + country code + city code + telephone number

To call Emergency Services:

Dial 911

Answering Calls

To answer incoming call:

Lift handset *or*
Press **Speaker** button *or*
Press **Headset** button *or*
Press **Answer** softkey *or*
Press the flashing line button

To answer second incoming call:

Press the flashing line button

Ending Calls

To end a call:

Replace handset *or*
Press **Speaker** button *or*
Press **Headset** button *or*
Press **End Call** softkey

Call Hold

To place call on hold:

Press **Hold** button

To retrieve held call:

Press **Hold** button *or*
Press **Resume** softkey *or*
Press flashing line button

To toggle between two held calls on same line:

Press flashing line button

To toggle between multiple held calls on same line:

1. Press flashing line button
2. Navigate to held call
3. Press **Resume** softkey

To toggle between held calls on shared line:

Press flashing line button

Call Forward

To immediately forward all calls to another number:

1. While on-hook press **Fwd All** softkey
2. Dial extension number *or*
Press the **Messages** button

To deactivate call forwarding:

Press **Fwd Off** softkey

Call Transfer

To transfer a call:

1. Press **Transfer** button
2. Dial extension
3. Optional: Announce caller
4. Press **Transfer** button *or*
Press **Transfer** softkey *or*
Hang up

If no answer or line is busy:

1. Press **Cancel** softkey
2. Press **Resume** softkey *or*
Press flashing line button

To toggle between calls:

Press **Swap** softkey

To transfer two calls on the same line to one another:

1. While connected to an active call, press **Transfer** button
2. Press flashing line button
3. Press **Yes** softkey to confirm and complete the transfer

To transfer a call to a subscriber's voicemail box:

1. Press **Transfer** button
2. Dial * and the mailbox number
3. Press **Transfer button** *or*
Transfer softkey *or*

Decline a Call

To immediately forward a ringing, live, or held call to voicemail:

Press the **Decline** softkey

Conference Calling

To place up to a 6-way conference call

1. While connected to an active call, press the **Conference** button
2. Dial the next participant
3. Optional: Announce the conference
4. Press **Conference** button *or*
Conference softkey again
5. Repeat to add more participants

To add an incoming caller to existing call or conference:

1. While connected to the incoming call, press the **Conference** button
2. Press the flashing line button
3. Press **Yes** softkey to confirm

To view conference participants:

1. Press **More (...)**
2. Press the **Details** softkey

To remove a participant:

1. Navigate to the participant
2. Press the **Remove** softkey

Need Help?

Contact the IT Service Center:

401-863-HELP (4357)
help@brown.edu

Related Content

- [Cisco 7841: Change Your Ringtone](#)
- [Cisco 7841: Conference](#)
- [Cisco 7841: View and Clear Call History](#)